


## STREET LIGHT BULB TYPE SL08. 18W TO REPLACE 55W SOX

Typically a 55W SOX LPS bulb will consume around 74W including ballast.

We have designed and developed an LED replacement bulb consuming only 19.0W and with similar dimensions to the original SOX bulb

By simply removing the ballast and fitting our SOXLED bulb into the existing head you benefit from lower power consumption, long life and therefore lower maintenance costs and the benefit of a high CRI giving a much better quality of light.



Type	SL08
LED	Bridgelux
LED Power	18W
Beam Angle	140°*80°
CRI	>70
Light Output	>1700Lm
Input Voltage	90-264V ac
Power Consumption	19.0W ± 5%
LED Life	>50,000 hours
Bulb Life	>35,000 hours
Base	B22d
Operating Temp	-30/+40°C
IP Grade	IP50
Material	Al+PC
Dimensions	Dia. 54mm*425mm
Weight	800g±10%
Available colours	
Warm White	2700-3500K
Daylight White	4000-5000K
Cool White	5500-6500K
Lux	
1.0m	620 lux
2.0m	153 lux
3.0m	80 lux
4.0m	55 lux
5.0m	42 lux
6.0m	34 lux
UK UMSUG No.	TBA

[www.magnatechled.com](http://www.magnatechled.com)

Mail: [info@magnatechled.com](mailto:info@magnatechled.com)

Magna Technology (Shenzhen) Co., Ltd.

Tel: +86 (0)755 6134 4368 Fax: +86 (0)755 6134 4369, Add: Suite 23D, Shangbu Dasha, Shangbu Road South, Futian, District, Shenzhen, China. 513081

Magnatech LED (UK) Ltd.

Tel: +44 (0)1223 834800 Fax: +44 (0)1220 834600, Add: Magna House, Dales Manor Business Park, Sawston, Cambridge CB22 3TJ, U.K.