

PLATEA PRO CODE: P879 / P881 / P883 / P885

VOLTAGE	DIMMING LEVEL	MEASURE MENTS	SAMPLE 1	SAMPLE 2	SAMPLE 3	SAMPLE 4	SAMPLE 5	WATT CURVE	VA CURVE
210	MIN % DIMMING	Watts	8.57	8.68	8.58	8.71	8.55	<p>Watt - 210V</p>	<p>VA - 210V</p>
		VA	12.94	12.98	13.02	13.04	12.75		
	40% DIMMING	Watts	24.04	24.15	23.97	24.02	24.11		
		VA	25.39	25.47	25.35	25.31	25.3		
	60% DIMMING	Watts	35.05	35.08	35.02	35.02	34.94		
		VA	36.42	36.48	36.46	36.37	36.29		
	80% DIMMING	Watts	46.96	47.1	46.9	47	46.92		
		VA	47.88	48.01	47.67	47.67	47.7		
	100% DIMMING	Watts	58.8	58.7	58.4	58.3	58.6		
		VA	59.64	59.46	59.22	59.22	59.16		
220	MIN % DIMMING	Watts	8.63	8.74	8.61	8.76	8.6	<p>Watt - 220V</p>	<p>VA - 220V</p>
		VA	13.34	13.38	13.38	13.51	13.09		
	40% DIMMING	Watts	24.14	24.18	24.08	24.05	24.16		
		VA	25.92	25.87	25.83	25.71	25.74		
	60% DIMMING	Watts	35.07	35.19	35.05	35.02	34.96		
		VA	36.78	36.74	36.74	36.74	36.61		
	80% DIMMING	Watts	46.93	47.14	46.9	46.9	46.92		
		VA	48.026	48.16	47.96	47.96	47.99		
	100% DIMMING	Watts	58.7	58.6	58.4	58.2	58.5		
		VA	59.62	59.62	59.4	59.4	59.34		
230	MIN % DIMMING	Watts	8.61	8.7	8.62	8.78	8.59	<p>Watt - 230V</p>	<p>VA - 230V</p>
		VA	13.85	13.83	13.89	13.92	13.57		
	40% DIMMING	Watts	24.22	24.31	24.14	24.11	24.22		
		VA	26.43	26.43	26.35	26.23	26.23		
	60% DIMMING	Watts	35.1	35.27	35.01	35.09	35		
		VA	37.19	37.28	37.12	37.12	36.96		
	80% DIMMING	Watts	46.94	46.99	46.9	47	46.93		
		VA	48.25	48.28	48.07	48.07	48.09		
	100% DIMMING	Watts	58.6	58.6	58.4	58.3	58.05		
		VA	59.8	59.8	59.57	59.57	59.57		
240	MIN % DIMMING	Watts	8.61	8.73	8.58	8.8	8.6	<p>Watt - 240V</p>	<p>VA - 240V</p>
		VA	15.07	14.98	15.1	14.86	14.64		
	40% DIMMING	Watts	24.29	24.36	24.2	24.16	24.28		
		VA	27.01	26.98	26.99	26.84	26.77		
	60% DIMMING	Watts	35.19	35.31	35.06	35.11	35.05		
		VA	37.61	37.73	37.54	37.61	37.12		
	80% DIMMING	Watts	46.97	47.06	47	46.9	46.92		
		VA	48.5	48.55	48.48	48.48	48.51		
	100% DIMMING	Watts	58.5	58.06	58.3	58.2	58.5		
		VA	60	60	59.8	59.76	59.8		
250	MIN % DIMMING	Watts	8.64	8.74	8.6	8.79	8.62	<p>Watt - 250V</p>	<p>VA - 250V</p>
		VA	15.72	15.67	15.77	15.83	15.37		
	40% DIMMING	Watts	24.34	24.45	24.28	24.25	24.32		
		VA	27.71	27.66	27.71	27.5	27.42		
	60% DIMMING	Watts	35.27	35.38	35.08	35.15	35.08		
		VA	38.15	38.25	38.05	38.1	37.88		
	80% DIMMING	Watts	47.02	47	47	46.9	47.02		
		VA	48.85	48.75	48.75	48.73	48.83		
	100% DIMMING	Watts	58.5	58.3	58.3	58.2	58.5		
		VA	60.25	60	60	60	60		